

## TRMA SERIES G2 SELECTABLE LED TROFFER

Client:  
Project:  
Type:  
Quantity:

### CONSTRUCTION

22-gauge metal frame, 95% reflective white polyester powder coat bonded to phosphate-free multi-stage pretreated metal. All parts painted after fabrication to facilitate installation, increase efficiency and inhibit corrosion. All corners are rounded for safe handling. Multiple wiring entrances on driver enclosure for easy access. Integral T-bar clips for installation into T-grid ceilings.



### OPTICS

Backlit design provides exceptional lighting distribution. Frosted polycarbonate lens offers edge to edge smooth illumination for maximum visual comfort.

### ELECTRICAL

Long-life LEDs, coupled with a high-efficiency driver, provide superior illumination for extended service life. Greater than 70% LED lumen maintenance at 60,000 hours (L70>60,000).

Selectable lumen and CCT technology allows easy field-adjustable capability, luminaire ships with maximum output and 4000K CCT setting.

All CCTs are within 3 MacAdam ellipses.

Driver operates at 120-277V input, 0-10V dimmable driver, down to 10%.

TRMA-G2-4

### SENSORS (OPTIONAL)

CONTROL-LVFA AVI-ON Bluetooth Mesh Controller

CONTROL-BLE-620 Bluetooth Wireless Fixture Controller for CCT Tuning,

Dimming, Grouping, Scheduling Features (ALS Control Mobile App)

### MOUNTING

Designed to accommodate lay-in ceilings, Slot T, and T-bar suspension system for 5/8" and 3/8" width.

Built-in earthquake clips come standard.

Surface/cable mount applications, use surface/cable kit accessories.

Plaster or sheetrock installations, select flange kit.

### STANDARD FINISH

Matte White finish.

### CERTIFICATION

Damp location label standard.

Meets Buy America Act requirements.

All luminaires are built to UL1598 standards and bear appropriate cULus labels.

For Emergency application, equipment with UL924 certified battery packs.

DLC® Premium (DesignLights Consortium Qualified).

### SHIPPING DATA

Product	Measurement	Weight
TRMA-G2-2 (2-pack)	25" L x 26" W x 3" H	15.5 lb
TRMA-G2-4 (2-pack)	50" L x 26" W x 3" H	32 lb

### WARRANTY

5 year warranty, see Limited Warranty for additional information.



## TRMA SERIES G2 SELECTABLE LED TROFFER

ORDER INFORMATION					EXAMPLE: TRMA 2 G2 WH UD			
Fixture	Series	Model	Finish	Input				
	TRMA		WH	UD				
<b>Mounting</b>								
<b>Accessories</b>								
<b>Options</b>								
<b>A</b>	<b>SERIES</b>							
TRMA	Selectable Lumen and CCT LED Metal Troffer							
<b>B</b>	<b>MODEL</b>							
Code	Size	Power	CCT					
2-G2	2x2	25W / 30W / 35W	3000K / 3500K / 4000K / 5000K					
4-G2	2x4	25W / 30W / 35W / 40W / 50W	3000K / 3500K / 4000K / 5000K					
<b>C</b>	<b>FINISH</b>							
WH	White							
<b>D</b>	<b>INPUT</b>							
UD	120-277V, 0-10V Dimming							
<b>G</b>	<b>MOUNTING</b>							
blank	Standard lay-in							
<b>MOUNT-LP-22-FGK</b>	1.52" Tall 2x2 Flange Kit (Plaster, Sheetrock or Drywall)							
<b>MOUNT-LP-24-FGK</b>	1.52" Tall 2x4 Flange Kit (Plaster, Sheetrock or Drywall)							
<b>MOUNT-LP-22-SMK</b>	4" Tall 2x2 Surface Mount Kit							
<b>MOUNT-LP-24-SMK</b>	4" Tall 2x4 Surface Mount Kit							
<b>H</b>	<b>ACCESSORIES/OPTIONS</b>							
AIA	Assembled in America, compliant with BAA (COTS)							
-C	3/8" x 6FT Steel Flex 5-18AWG Solid 6' leads BLK/WH/GRN/PUR/PNK & 3/8" Die Cast Screw-In Locknut Connectors							
<b>CONTROL-LVFA*</b>	AVI-ON Bluetooth Mesh Control System							
<b>CONTROL-BLE-620*</b>	Bluetooth Wireless Fixture Controller for CCT Tuning, Dimming, Grouping, Scheduling Features (ALS Control Mobile App)							
<b>EMB-18W-B*</b>	90-Minute Self-Diagnostic Emergency Battery 18W 100-347VAC Input 170VDC Output							
<b>GTD-ESRLUD**</b>	Emergency Battery Generator Transfer Device 120-277 VAC Input							


\*see page 5 for sensor and emb spec

\*\*see page 8 and 9 for GTD spec

## TRMA SERIES G2 SELECTABLE LED TROFFER

### DIMENSIONS

Model	L	W	D
TRMA-G2-2	23.74" (603mm)	23.74" (603mm)	1.80" (45mm)
TRMA-G2-4	47.76" (1213mm)	23.74" (603mm)	1.80" (45mm)



## TRMA SERIES G2 SELECTABLE LED TROFFER

### PERFORMANCE DATA

SYSTEM WATTS	SIZE	VOLTAGE	LUMEN	LPW	QTY ON PALLET
25W	2x2	120-277V	3250	130	120
	2x4	120-277V	3250	130	120
30W	2x2	120-277V	3900	130	120
	2x4	120-277V	3900	130	120
35W	2x2	120-277V	4550	130	120
	2x4	120-277V	4550	130	120
40W	2x4	120-277V	5200	130	60
50W	2x4	120-277V	6500	130	60

## TRMA SERIES G2 SELECTABLE LED TROFFER

### SENSOR SPEC

Model	Type	Mounting	Coverage	Input	Function	Programmable
CONTROL-LVFA (see page 6 for detail)	Fixture Controller	-	-	12V DC	Bluetooth Mesh On/Off/Dimming Scheduling	AVI-ON Bluetooth Mobile App
CONTROL-BLE-620 (see page 7 for detail)	Fixture Controller	Integral to Fixture	-	12V DC	CCT Tuning Dimming Grouping Time Schedule	ALS Control Bluetooth Mobile App




CONTROL-BLE-620

CONTROL-LVFA


### EMB SPEC

Model	Battery Capacity	Input	Output	Output Power	Operating Temp	Installation
EMB-18W-B	90mins	100-347VAC	170VDC	18W	0°C ~ 50°C 32°F ~ 122°F	Factory or Field Install



## TRMA SERIES G2 SELECTABLE LED TROFFER

### CONTROL-LVFA SPEC




### SPECIFICATIONS

<b>INPUT VOLTAGE:</b>	12-24VDC
<b>CURRENT:</b>	15mA without a Sensor
	19mA with a DC PIR Sensor
	48mA with a DC Microwave Sensor
<b>0-10V DIMMING:</b>	12-24VDC
<b>SIZE:</b>	2.30in x 1.43in x 0.75in (58.2mm x 36.4mm x 19mm)
<b>MOUNTING:</b>	Removable mounting tabs
<b>WEIGHT:</b>	0.45 oz (16g)
<b>OPERATING TEMP:</b>	-22°F to +158°F (-30°C to + 70°C)


<b>RADIO FREQUENCY:</b>	2.4GHz
<b>WIRELESS STANDARD:</b>	BLE 4.2 with Mesh
<b>POINT TO POINT RANGE*:</b>	80ft with obstructions 350ft unobstructed
<b>SECURITY:</b>	AES 128-bit encryption for device to device communication AES 256-bit encryption for device to cloud communication
<b>WARRANTY:</b>	5 years; 10 years optional
<b>REGULATORY:</b>	FCC: 2AFZ1-AV11010 B IC: 20544-AV11010 B BQB: D031801, DID: 86303 UL 916, 2043 (Plenum Rated)

\*When communicating through the mesh, range is essentially unlimited (5000ft+)

### WIRING DIAGRAM



Fixture adapter powered by LED driver auxiliary output



Fixture adapter connected to LED driver and using power supply

## FEATURE

- **Installation:** Factory installed, 12V AUX power required
- **Commissioning:** Wirelessly through ALS Control Mobile App (iOS / Android)
- **Certification:** DLC 5.1 Networked Lighting Control System
- **Control:** Dimming, High-End Trim, Zoning, Continuous Bi-level Dimming
- **CCT Tuning:** CCT Tuning feature for Dual/Multi-CCT LED board fixture only
- **Sensor:** Plug-N-Play with ALS Control sensors
- **Zone Control:** Zoning and Grouping control, Scheduling



## SPECIFICATIONS

### WIRELESS STANDARDS:

5.0 Bluetooth Mesh

### INPUT VOLTAGE:

12-14VDC, >50mA

### OUTPUT VOLTAGE:

LED Max. 150VDC Max. 2A

### CONTROL OUTPUT:

0-10V

### OPERATING TEMP:

-40°F ~ +158°F (-40°C ~ +70°C)

### COMMISSIONING RANGE:

50FT

### BLUETOOTH RANGE:

100FT


### WARRANTY:

5 years

### IP RATING:

IP20

## DIMENSIONS




L	H	W
3.5" (89mm)	0.43" (11mm)	1.00" (26mm)

Lead Wire	Antenna Wire
10.60" (270mm)	10.60" (270mm)

## WIRING DIAGRAM



## GTD-ESRLUD Generator Transfer Device

Client:  
Project:  
Type:  
Quantity:

### CONSTRUCTION

Yellow metal casing. Integrates with dry contact systems to provide lighting during power outages. Features a slim enclosure, allowing for seamlessly integrating into existing building infrastructure.

Designed for commercial and industrial applications that require an emergency load to be switched on during a loss of normal power.



### SPECIFICATIONS

COIL CURRENT:	Normal Power = 6mA MAX
COIL VOLTAGE INPUT:	120-277V AC (50/60 Hz)
EXPECTED RELAY LIFE:	10 Million Cycles Min Mechanical
RELAY CONTACT RATINGS:	10 Amp Resistive @ 30 V DC 10 Amp General Use @ 277 V AC
OPERATING TEMP:	-30°F ~ +140°F (-34°C ~ +60°C)
OPERATE TIME:	18ms
HUMIDITY RANGE:	5-95% (Noncondensing)
LED:	Green = Normal Power Red = Relay Status
DIMENSIONS:	1.40" H x 5.63" W x 1.00" D
WIRES:	16", 600V Rated
OVERRIDE (TEST SWITCH):	No
APPROVALS:	UL924, C-UL, CE, ROHS
NOTES:	Device Draws no Current From Emergency Source

### TESTING

INITIAL TEST FOR CORRECT WIRING:	Apply Normal Power To Normal Power Input a. Green LED (Normal Power) should be ON b. Red LED (Relay Status) should be ON c. Load should be OFF d. Relay Contact (N/O) should be CLOSED
LOCAL TEST BUTTON:	1. Turn Switched Circuit OFF. Load be OFF. 2. Press and Hold "Local Test Button" 3. Load should Turn ON 4. Release "Local Test Button" and Emergency Light should Turn OFF.
WALL SWITCH:	1. Turn ON Wall Switch If not already ON 2. Load should Turn ON 3. Turn Wall Switch OFF 4. Load will Turn OFF


### TROUBLESHOOTING

CONDITION	ACTION
Green LED is OFF	<ul style="list-style-type: none"> <li>Check Normal Power Input Wiring (Black and Red Wires) and Voltage.</li> </ul>
Red LED is OFF but Load is OFF	<ul style="list-style-type: none"> <li>Check Bulbs and Ballast.</li> <li>Check Load Wiring (Blue Wire and Load's Neutral).</li> <li>Replace Unit. (Assuming N/C Contact is Used).</li> </ul>
Load is ON but Red LED is ON	<ul style="list-style-type: none"> <li>Replace Unit. (Assuming N/C Contact is Used).</li> </ul>
Red LED does not Turn OFF and Load does not Turn ON when being tested	<ul style="list-style-type: none"> <li>Check Bulbs and Ballast.</li> <li>Check Wiring Connections if Using a Remote Test Option.</li> <li>Press Local Test Button on the Unit.</li> <li>Replace Unit.</li> </ul>
Red LED will not Turn ON and Load will not Turn OFF	<ul style="list-style-type: none"> <li>Verify Status of Normal Power Input.</li> <li>Open Wall Switch Input.</li> <li>Verify That No Test Inputs are Stuck Closed.</li> </ul>

## GTD-ESRLUD Generator Transfer Device

### WIRING DIAGRAM

#### USING EMERGENCY LIGHTING AS NORMAL LIGHTING



#### OVERRIDING A 0-10V DIMMER

