

PLEASE READ AND FOLLOW ALL SAFETY INSTRUCTIONS**SAVE THIS SHEET****To Avoid Risk of Electric Shock and Injury**

- Never attempt any work on the luminaire unless it is disconnected from the power source.
- Any Installation and service of the luminaire should be done by a certified electrician.
- Confirm the supply voltage matches the voltage labeled on the luminaire.
- Make sure all electrical and grounded connections are in accordance with the National Electric Code (NEC) and any local codes.
- Make sure all connections are capped with UL-listed wire connectors.
- Allow luminaire to cool down before handling. Never handle luminaire when it is in use.
- Do not exceed the maximum wattage labeled on luminaire.
- Always wear gloves and safety glasses when installing, handling, or performing routine maintenance on the luminaire.
- Do not look directly at the light source when luminaire is on.

To Avoid Risk of Fire and Product Damage

- Keep any combustible material away from the luminaire.
- Do not operate luminaire near any persons, materials, or substances that are sensitive to heat.
- When mounting, make sure wiring is secured from any edges or objects that can damage the wire insulation.
- Do not obstruct ventilation of the luminaire. Do not cover the luminaire with foam or other insulation material that will restrict convection or conduction cooling.
- Only use luminaire at its intended location.
- LED fixtures are sensitive to polarity. Make sure to identify proper polarity before installing.
- Electrostatic Discharge (or ESD) can damage LED luminaire. Make sure to always wear personal grounding equipment when installing or servicing the luminaire.
- Avoid touching individual electrical components, which can cause ESD and will reduce the life and performance of the luminaire.
- Do not power luminaire on and off frequently as this will greatly reduce luminaire's lifespan.
- Always read the luminaire's complete installation instruction sheet before installing luminaire.
- Always inspect the luminaire for damage. DO NOT INSTALL fixture if there is any damage. Contact your distributor or representative where you purchased the luminaire for warranty claim if luminaire is damaged.

To Maintain Luminaire and Ensure Consistent Performance

- **IMPORTANT: Always make sure luminaire is disconnected from power source when performing routine maintenance.**
- Occasionally clean luminaire lens. When cleaning lens, you may dust with soft, dry and clean cloth. You may also use solution of warm water and non-abrasive cleaning agent then wipe with dry cloth. DO NOT USE alkaline or acid cleaners.
- Keep heatsink clear of dust or debris from time to time.
- Maintaining the luminaire on a routine basis is highly recommended.

Failure to follow any of these instructions may void warranty.


Please visit www.alslighting.us to view complete product Terms and Conditions.

Advantage Lighting Solutions assumes no responsibility for claims arising from improper or careless installation or handling of its products.

Important Safety Instructions

1. Make sure power is turned OFF before installing.
2. Inspect fixture for any damages. If damaged, DO NOT install fixture and contact local ALS distributor immediately.

Hardware Content




	CONTENTS	2ft/4ft	8ft
A	V-HOOK	2	3
B	SURFACE MOUNT BRACKET	2	3
C	PLASTIC TUBE-6*31mm	2	3
D	SELF-DRILLING SCREW-4*32*7	2	3
E	METEL GASKET-4*12*0.7	2	3
F	RUBBER GASKET-4*12*1	2	3
G	PLUG	1	1
H	SEALING RING	1	1
I	NUT	1	1

Note:


[1] Connect the flexible cord (SJTW 18AWG, not included) to the driver input wires. Be sure to connect the wet location rated strain relief (included) to the Knock-out on the housing.

A: Surface Mounting


1. Release latches by pulling top of latch away from the housing. Detach LED tray and lens from fixture.




3. Reattach LED tray and lens to fixture by reversing step 1.




2. Connect power cord to driver as below figure shown [1]. (the flexible cord supplied by others).




4. Locate and drill holes, then install clips to the ceiling surface using hardware found in hardware kit.



5. Connect fixture to AC power refer to General Wiring Diagram.




6. Press fixture housing to the clips until both sides of the housing recesses are secured.




B: Chain Suspended Mounting


1. Release latches by pulling top of latch away from housing. Detach LED tray and lens from fixture.




2. Connect an appropriate length of power cord to driver as shown in below figure^[1]. (the flexible cord supplied by others)



3. Secure mounting clips to fixture housing recesses by firmly pressing them into place, then attach V-hooks to each mounting clip.




4. Hang the fixture by attaching the V-hooks to chains. Make wiring connection to Power supply accord to local laws and regulations.




C: Cable Suspended Mounting


1. Release latches by pulling top of latch away from housing. Detach LED tray and lens from fixture.




3. Secure mounting clips to fixture housing recesses by firmly pressing them into place.



2. Connect an appropriate length of power cord to driver as shown in below figure^[1]. (the flexible cord supplied by others)



4. Attach the ends of aircraft cable to the clips as shown. Adjust aircraft cable to make fixture at a proper height by quick cable-lock. Make wiring connection to Power supply accord to local laws and regulations.



General Wiring Diagram

